



## Contents

Contents. . . . .	1
Important note. . . . .	2
Control elements. . . . .	3
Rear panel features introduction. . . . .	4
Rear panel features introduction. . . . .	5
Audio input and output connections. . . . .	6
PC Interface. . . . .	7
Professional Power Amplifier Specifications. . . . .	8

## SPECIFICATION

### DSP

MODEL:	D6Q D10Q
Input:	4 channel
Output:	4 channel
PC Com Port:	1 USB Com Port on front panel, 1 USB Com Port, 2 RS485 Com Port on back panel (RJ-45)
Processor:	48KHz Sampling frequency, 48-bit Fixed-Point DSP, 24-bit A/D and D/A converter
Dynamic range:	>110dB
Frequency Response:	±0.25dB, 20Hz---20KHz
Distortion:	< 0.01%, 20Hz-20KHz @ +10dBu balanced input
Signal to noise ratio:	>110dB
cross over filter:	Each output channel can be independently set as LPF and HPF, The parameters can be adjusted, Filter type: Butterworth, Bessel, Linkwitz-Riley, The Crossover Frequency: 20Hz---20KHz, Slope: 12, 18, 24 or 48 dB/octave
EQ:	Bandwidth: 0.2 to 36 oct, Frequency: 20Hz to 20KHz, Gain: -24dB to +12dB, step: 0.2 dB
Delay:	0ms to 115ms
Display:	2 x 20 LCD
Store Settings:	20 user program dynamic storage

### AMPLIFIER

Model	D6Q	D10Q
<b>Output Power</b>		
8 Ω Stereo Power	4×625W	4×1300W
4 Ω Stereo Power	4×1250W	4×2200W
2 Ω Stereo Power	4×1500W	4×2500W
8 Ω Bridged Monon Power	2×2500W	2×4400W
4 Ω Bridged Monon Power	2×3000W	2×5000W
Frequency Response	20Hz-20kHz ±0.5dB	
THD+N(Rated power, 4Ω/KHz)%	0.10%	
Signal Noise Ration(dB)	110dB	
Input Impedance	20KΩ Balanced / 10kΩ Unbalanced	
Output Connectors	Speakon Connectors (NEUTRIK)	
Power Requirement	100-120V-50-60Hz or 200-240V-50-60Hz	

<b>Dimension</b>	
Airframe	483×377×88mm
Weight	
Weight(net)	13Kg

## Important Note

### **WARNING NOTICES**

#### **SAFEGUARDS**

Electrical energy can perform many useful functions, This unit has been engineered and manufactured to assure your personal safety. Improper use can result in potential electrical shock or fire hazards. In order not to defeat the safeguards, observe the following precautions for its installation, use and servicing.

#### **Explanation of Graphical Symbols**



**CAUTION  
RISK OF ELECTRIC SHOCK  
DO NOT OPEN**



**CAUTION  
RISK OF ELECTRIC SHOCK:  
OPEN ONLY IF QUALIFIED  
AS SERVICE PERSONNEL**

**WARNING: TO PREVENT FIRE OR ELECTRIC SHOCK, DO NOT EXPOSE  
THIS EQUIPMENT TO RAIN OR MOISTURE**


### **IMPORTANT NOTE**

**ATTENTION:** This unit must be protected from damp because of the risk of fire and the possibility of electric shocks.

1. Make sure that you have the correct mains voltage. Only operate the unit at the mains voltage marked on the rear panel.
2. Make sure that nothing especially no metal objects are inserted into the device. This could result in electric shock or malfunction.
3. If the unit is subjected to extreme fluctuations of temperature e.g. On being transported from outside into a heated room, condensation can form. This unit should not be used until it has reached room temperature.
4. In the event of water or any other fluid being accidentally spilt on the unit switch the unit off immediately and send it to a qualified service workshop for inspection.
5. Make sure that the unit is always well ventilated and never exposed to direct sunlight
6. Do not use sprays to clean the unit as they have a detrimental effect on the unit and could ignite suddenly.
7. The machine use single power switch, please cut off the power before fix.
8. Please do not put the cup, vessel of flower or container above the machine, in case the leak out water then cause the leakage current off the machine.

## Control elements

### Introduction of the front panel functions



#### Signal indicator

**SIGNAL LED:** Indicate output signal levels in normal operating range

**VPL LED:** This indicator signals if the amplifier output is clipping or limiting.

**CPL LED:** Low impedance/Short Circuit Detection Fault

**MUTE LED:** MUTE-Audio protection under mute position.

#### LED display

Turn on the power supply, display light can display various parameters for use's convenience

#### Enter

Confirm the parameter you are setting or enter into operation menu

#### Back

To page up or move the cursor when edit

#### Next

To page down or move the cursor when edit

#### Menu

In standby state, press this key to enter the system setup program

#### Input channel setting key

Click this key to make current channel MUTE or Sound On.

Push this key 3 seconds to enter into this channel's setting mode

#### USB interface

Use a USB cable to connect the machine and PC

#### Output channel setting key

Click this key to make current channel MUTE or Sound On.

Push this key 3 seconds to enter into this channel's setting mode

#### ESC

Back to previous menu when click ESC in edit state or return to stand-by under other conditons

#### Control Knob

Set parameters in edit state

#### Bypass


Choose to open or close when editing EQ Adjusted parameter is not implemented under bypass condition

#### Power switch

Turn the unit power on or off.




## Rear panel features introduction




- Mains input 200V-240V or 100V-120V operation
- 2 channel version shown with Neutrik Speakon output connectors
- DSP control Port
- XLR connectors for inputs and loop thru
- 4channel version shown with Neutrik Speakon output connectors

### Input Connectors




Audio inputs-4-channel models



### Audio link:


the signal input into channel 1 can be output from channel 1 only, similarly, the signal channel 3 is the same.

### Output Connectors




## Rear panel features introduction

### Speakon outputs-4-channel models



**Four-channel amplifiers** Additional connectors are provided for channel 3 and channel 4. Channel 3 functions as channel 1 above, and channel 4 as channel 2 above.


### BALANCED INPUT CONNECTIONS



Audio input-4-channel models


The XLR input connectors are electronically balanced, and wired according to the IEC 268 standard ( pin 2= hot ). XLR input connectors should be wired follows:

- Pin 1 Ground/Shield
- Pin 2 Hot (+)
- Pin 3 Cold (-)



When linking the same source signal to several input channels, be aware that there is a limit to the number of channels an output source can "drive". A typical output source (e.g. a DSP crossover unit) can drive up to four amplifier channels before external line-drivers might be required to buffer the signal.

### Unbalanced Input connections




To connect an input to an unbalanced source, it is possible to connect pins 1 and 3 in the XLR plug at the amplifier end of the cable. However, a better method is to connect pin 3 to the shield at the source end of the cable, as this usually results in better hum and noise rejection. Balanced input connections are recommended whenever possible



## Audio input and output connections


### Route

The signal input into any channel can be select output from any channel.




### Stereo Mode

The signal input into channel 1 can be output from channel 1 only, similarly, the signal input into channel 2 can be output from channel 2 only. The many channels, one by one in order type pushes.



### Bridge Mode

channel 1 and channel 2 are bridged,  
channel 3 and channel 4 are bridged.





## PC Interface

Connection type

Work mode

Show or hidden Curve

Input signal indicator

Synchronized regulation

Rename input

Input parameter copy

Output signal indicator

Synchronized regulation

Output parameter copy

Rename output

DSP系列

V 2.2.1.H

Connected

Disconnected

V 2.2.1.H

Current Mode: Normal

System

15dB

-10dB

+5dB

0dB

-5dB

-10dB

-15dB

-20dB

-25dB

-30dB

20Hz

50Hz

100Hz

200Hz

500Hz

1KHz

2KHz

5KHz

10KHz

20KHz

Linked

In A Mute Pol+ Gain EQ XOver

In B Mute Pol+ Gain EQ XOver

In C Mute Pol+ Gain EQ XOver

In D Mute Pol+ Gain EQ XOver

Route Mute Pol+ Gain Delay EQ XOver Limiter

Out 1

Out 2

Out 3

Out 4

Copy In A To In A OK

Copy Out 1 To Out 1 OK

485

Disconnected

V 2.2.1.H

485

Ethernet

Device ID 1

485 ID NUMBER

Ethernet

Disconnected

V 2.2.1.H

Local IP: 192.168.1.4

IP Address: [ ] [ ] [ ] [ ] [ ] [ ]

Search

DeviceIP\_List

Device List

(Please wait for a few seconds, the search will take some time)

The device can be connected (Press "Search" button will refresh the list.)

No.	IP Address	Name
1	192.168.1.100	Device #1







IP Address: 192 168 1 100

Device #1


Connect

Choose

## PC Interface      Network application



## Cable connection



## Wifi connection

